

## Kaevanduses kasutatavad ventilaatorid

**EAC**



**EMT**



**ELF**



**RFC seeria**



**EGM**



| Tüüp   | Võimsus (kW) | Pinge (V)  | Vool (A) | Pöörete arv (x/min) | Õhukogus (m <sup>3</sup> /h) | Surve max Pa | Kaal (kg) | Mürategur (dB) | Töötempe ratuur (C) | IP kaitseaste |
|--|--------------|------------|----------|---------------------|------------------------------|--------------|-----------|----------------|---------------------|---------------|
| <a href="#">EAC/2-315-025x</a><br><a href="#">OII2</a><br><a href="#">GcT3</a><br><a href="#">IP5x</a>                     | 0.25         | 400V, 50Hz | 0.7      | 2770                | 2800                         | 500          | ---       | ---            | -20 +40             | IP5x          |
| <a href="#">EAC/2-355-055x</a><br><a href="#">O</a><br><a href="#">II2G</a><br><a href="#">cT3</a><br><a href="#">IP5x</a> | 0.55         | 400V, 50Hz | 1.4      | 2720                | 3600                         | 600          | ---       | ---            | -20 +40             | IP5x          |
| <a href="#">EAC/2-400-110x</a><br><a href="#">O</a><br><a href="#">II2G</a><br><a href="#">cT3</a><br><a href="#">IP5x</a> | 1.1          | 400V, 50Hz | 2.4      | 2780                | 6400                         | 700          | ---       | ---            | -20 +40             | IP5x          |
| <a href="#">EAC/2-450-110x</a><br><a href="#">OII2</a><br><a href="#">GcT3</a><br><a href="#">IP5x</a>                     | 1.1          | 400V, 50Hz | 2.4      | 2780                | 7300                         | 600          | ---       | ---            | -20 +40             | IP5x          |
| <a href="#">EAC/2-500-220x</a><br><a href="#">O</a><br><a href="#">H2Gc</a><br><a href="#">T3</a>                          | 0.75         | 400V, 50Hz | 1.9      | 1430                | 8600                         | 170          | ---       | ---            | -20 +40             | IP5x          |

|  |     |               |      |      |       |      |     |     |         |      |
|--|-----|---------------|------|------|-------|------|-----|-----|---------|------|
| <a href="#"><u>IP5x</u></a>  |     |               |      |      |       |      |     |     |         |      |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>2-</u></a><br><a href="#"><u>500-</u></a><br><a href="#"><u>220x</u></a><br><a href="#"><u>Q</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T4</u></a><br><a href="#"><u>IP5x</u></a>                              | 2.2 | 400V,<br>50Hz | 4.5  | 2870 | 10000 | 800  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>2-</u></a><br><a href="#"><u>560-</u></a><br><a href="#"><u>400</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5x</u></a>                              | 4   | 400V,<br>50Hz | 7.5  | 2875 | 14000 | 1100 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>2-</u></a><br><a href="#"><u>560-</u></a><br><a href="#"><u>400</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T4</u></a><br><a href="#"><u>IP5x</u></a>                              | 4   | 400V,<br>50Hz | 7.5  | 1890 | 14000 | 1100 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>2-</u></a><br><a href="#"><u>630-</u></a><br><a href="#"><u>700x</u></a><br><a href="#"><u>Q</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5x</u></a>                              | 7   | 400V,<br>50Hz | 12.7 | 2920 | 22000 | 1200 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>2-</u></a><br><a href="#"><u>630-</u></a><br><a href="#"><u>750x</u></a><br><a href="#"><u>Q</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T4</u></a><br><a href="#"><u>IP5x</u></a>                              | 7.5 | 400V,<br>50Hz | 14   | 2920 | 22000 | 1200 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>4-</u></a><br><a href="#"><u>1000</u></a><br><a href="#"><u>-</u></a><br><a href="#"><u>1100</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5x</u></a> | 11  | 400V,<br>50Hz | 21.2 | 1460 | 49000 | 440  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>4-</u></a><br><a href="#"><u>1000</u></a><br><a href="#"><u>-</u></a><br><a href="#"><u>1100</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a>   | 11  | 400V,<br>50Hz | 20.5 | 1460 | 49000 | 440  | --- | --- | -20 +40 | IP5x |

|  |      |               |     |      |       |      |     |     |         |      |
|--|------|---------------|-----|------|-------|------|-----|-----|---------|------|
| <a href="#">T4</a><br><a href="#">IP5x</a>   |      |               |     |      |       |      |     |     |         |      |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">315-</a><br><a href="#">012x</a><br><a href="#">Q</a><br><a href="#">II2G</a><br><a href="#">cT3</a><br><a href="#">IP5x</a> | 0.12 | 400V,<br>50Hz | 0.5 | 120  | 3150  | 75   | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">355-</a><br><a href="#">012x</a><br><a href="#">Q</a><br><a href="#">II2G</a><br><a href="#">cT3</a><br><a href="#">IP5x</a> | 0.12 | 400V,<br>50Hz | 0.5 | 1380 | 2800  | 95   | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">400-</a><br><a href="#">025x</a><br><a href="#">OII2</a><br><a href="#">GcT3</a><br><a href="#">IP5x</a>                     | 0.25 | 400V,<br>50Hz | 0.8 | 1350 | 13500 | 110  | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">450-</a><br><a href="#">037</a><br><a href="#">xO</a><br><a href="#">II2G</a><br><a href="#">cT3</a><br><a href="#">IP5x</a> | 0.37 | 400V,<br>50Hz | 1.3 | 1350 | 6000  | 160  | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">500-</a><br><a href="#">055x</a><br><a href="#">Q</a><br><a href="#">H2Gc</a><br><a href="#">T3</a><br><a href="#">IP5x</a>  | 0.55 | 400V,<br>50Hz | 1.6 | 1370 | 8000  | 1370 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">500-</a><br><a href="#">075x</a><br><a href="#">Q</a><br><a href="#">H2Gc</a><br><a href="#">T4</a><br><a href="#">IP5x</a>  | 0.75 | 400V,<br>50Hz | 1.9 | 1430 | 8600  | 170  | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">4-</a><br><a href="#">560-</a><br><a href="#">110x</a><br><a href="#">OII2</a><br><a href="#">GcT3</a><br><a href="#">IP5x</a>                     | 1.1  | 400V,<br>50Hz | 2.7 | 1405 | 12000 | 200  | --- | --- | -20 +40 | IP5x |

|   |     |               |      |      |       |     |     |     |         |      |
|---|-----|---------------|------|------|-------|-----|-----|-----|---------|------|
| <a href="#">EAC/4-560-110x OII2 GcT4 IP5x</a> | 1.1 | 400V,<br>50Hz | 2.8  | 1405 | 12000 | 200 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-630-150x Q H2Gc T3 IP5x</a> | 1.5 | 400V,<br>50Hz | 3.7  | 1415 | 14800 | 250 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-630-150x Q H2Gc T4 IP5x</a> | 1.5 | 400V,<br>50Hz | 3.6  | 1415 | 14800 | 250 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-710-400x OII2 GcT3 IP5x</a> | 4   | 400V,<br>50Hz | 8.3  | 1430 | 24000 | 300 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-710-400x OII2 GcT4 IP5x</a> | 4   | 400V,<br>50Hz | 8.4  | 1430 | 24000 | 300 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-800-550x Q H2Gc T3 IP5x</a> | 5.5 | 400V,<br>50Hz | 11.1 | 1445 | 32000 | 400 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-800-550x Q H2Gc T4 IP5x</a> | 5.5 | 400V,<br>50Hz | 11.1 | 1445 | 32000 | 400 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/4-900-750</a>                 | 7.5 | 400V,<br>50Hz | 14.6 | 1450 | 38000 | 500 | --- | --- | -20 +40 | IP5x |

|   |      |               |      |      |       |     |     |     |         |      |
|---|------|---------------|------|------|-------|-----|-----|-----|---------|------|
| <a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5x</u></a>  |      |               |      |      |       |     |     |     |         |      |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>4-</u></a><br><a href="#"><u>900-</u></a><br><a href="#"><u>750</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T4</u></a><br><a href="#"><u>IP5x</u></a>   | 7.5  | 400V,<br>50Hz | 14.8 | 1450 | 38000 | 500 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>6-</u></a><br><a href="#"><u>560-</u></a><br><a href="#"><u>025</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5x</u></a>   | 0.25 | 400V,<br>50Hz | 1    | 870  | 7700  | 70  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>6-</u></a><br><a href="#"><u>1000</u></a><br><a href="#"><u>-400</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>H2Gc</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5x</u></a>  | 4    | 400V,<br>50Hz | 8.5  | 950  | 38500 | 200 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>6-</u></a><br><a href="#"><u>1000</u></a><br><a href="#"><u>-400</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>II2G</u></a><br><a href="#"><u>cT4</u></a><br><a href="#"><u>IP5x</u></a> | 4    | 400V,<br>50Hz | 9.4  | 950  | 38500 | 200 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>6-</u></a><br><a href="#"><u>1250</u></a><br><a href="#"><u>=</u></a><br><a href="#"><u>1100</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>II2G</u></a><br><a href="#"><u>cT3...</u></a> | 11   | 400V,<br>50Hz | 22   | 980  | 59000 | 400 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>6-</u></a><br><a href="#"><u>1250</u></a><br><a href="#"><u>=</u></a><br><a href="#"><u>1100</u></a><br><a href="#"><u>xO</u></a><br><a href="#"><u>II2G</u></a><br><a href="#"><u>cT4...</u></a> | 11   | 400V,<br>50Hz | 24   | 980  | 59000 | 400 | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/</u></a><br><a href="#"><u>6-</u></a><br><a href="#"><u>500-</u></a><br><a href="#"><u>018x</u></a><br><a href="#"><u>Q</u></a>  | 0.18 | 400V,<br>50Hz | 0.8  | 890  | 5900  | 50  | --- | --- | -20 +40 | IP5x |

|  |      |               |      |     |       |     |     |     |         |      |
|--|------|---------------|------|-----|-------|-----|-----|-----|---------|------|
| <a href="#">H2Gc</a><br><a href="#">T3</a><br><a href="#">IP5x</a>   |      |               |      |     |       |     |     |     |         |      |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">630-</a><br><a href="#">037</a><br><a href="#">xO</a><br><a href="#">H2Gc</a><br><a href="#">T4</a><br><a href="#">IP5x</a>  | 0.37 | 400V,<br>50Hz | 1.2  | 910 | 10200 | 90  | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">630-</a><br><a href="#">037x</a><br><a href="#">O</a><br><a href="#">H2Gc</a><br><a href="#">T3</a><br><a href="#">IP5x</a>  | 0.37 | 400V,<br>50Hz | 1.3  | 910 | 10200 | 90  | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">710-</a><br><a href="#">055x</a><br><a href="#">OII2</a><br><a href="#">GcT3</a><br><a href="#">IP5x</a>                     | 0.55 | 400V,<br>50Hz | 1.7  | 880 | 12000 | 120 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">710-</a><br><a href="#">055x</a><br><a href="#">OII2</a><br><a href="#">GcT4</a><br><a href="#">IP5x</a>                     | 0.55 | 400V,<br>50Hz | 0.55 | 880 | 12000 | 120 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">800-</a><br><a href="#">150x</a><br><a href="#">O</a><br><a href="#">H2Gc</a><br><a href="#">T3</a><br><a href="#">IP5x</a>  | 1.5  | 400V,<br>50Hz | 4.1  | 945 | 20000 | 170 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">800-</a><br><a href="#">150x</a><br><a href="#">O</a><br><a href="#">II2G</a><br><a href="#">cT4</a><br><a href="#">IP5x</a> | 1.5  | 400V,<br>50Hz | 4.3  | 945 | 20000 | 170 | --- | --- | -20 +40 | IP5x |
| <a href="#">EAC/</a><br><a href="#">6-</a><br><a href="#">900-</a><br><a href="#">300</a><br><a href="#">xO</a><br><a href="#">H2Gc</a><br><a href="#">T3</a><br><a href="#">IP5x</a>  | 3    | 400V,<br>50Hz | 6.8  | 945 | 29000 | 220 | --- | --- | -20 +40 | IP5x |

|   |      |               |     |      |       |      |     |     |         |      |
|---|------|---------------|-----|------|-------|------|-----|-----|---------|------|
| <a href="#"><u>EAC/6-900-300xO II2G cT4 IP5x</u></a>  | 3    | 400V,<br>50Hz | 6.9 | 945  | 29000 | 220  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/8-1000-220xO II2G cT4 IP5x</u></a> | 2.2  | 400V,<br>50Hz | 5.7 | 710  | 34000 | 110  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/8-1250-750xO II2G cT4 IP5x</u></a> | 7.5  | 400V,<br>50Hz | 17  | 720  | 6400  | 220  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/8-710-037xO II2G cT4 IP5x</u></a>  | 0.37 | 400V,<br>50Hz | 1.9 | 690  | 11000 | 40   | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/8-800-075xO II2G cT4 IP5x</u></a>  | 0.75 | 400V,<br>50Hz | 2.6 | 700  | 17500 | 500  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EAC/8-900-150xO II2G cT4 IP5x</u></a>  | 1.5  | 400V,<br>50Hz | 5.3 | 710  | 25000 | 120  | --- | --- | -20 +40 | IP5x |
| <a href="#"><u>EMT-290 II 2D c T125 C ATEX</u></a>    | 4    | 400V          | 7.8 | 2875 | 3700  | 3252 | 61  | --- | -20 +60 | IP5x |
| <a href="#"><u>EMT-290</u></a>                        | 4    | 400V          | 7.5 | 2875 | 3700  | 3252 | 62  | --- | -20 +60 | IP5x |

|   |     |      |      |      |      |      |      |     |         |      |
|---|-----|------|------|------|------|------|------|-----|---------|------|
| <a href="#">II 2G</a><br><a href="#">c T3</a><br><a href="#">IP5X</a>   |     |      |      |      |      |      |      |     |         |      |
| <a href="#">EMT-290</a><br><a href="#">II 2G</a><br><a href="#">c T4</a><br><a href="#">IP5X</a>                        | 4   | 400V | 7.8  | 2875 | 3700 | 3252 | 83.7 | --- | -20 +60 | IP5x |
| <a href="#">EMT-290</a><br><a href="#">II 3G</a><br><a href="#">c T3</a><br><a href="#">IP5X</a>                        | 4   | 400V | 7.5  | 2875 | 3700 | 3252 | 62   | --- | -20 +60 | IP5x |
| <a href="#">EMT-160</a><br><a href="#">II 2D</a><br><a href="#">c T125</a><br><a href="#">C</a><br><a href="#">ATEX</a> | 2.2 | 400V | 4.6  | 2860 | 2040 | 2250 | 37.9 | --- | -20 +60 | IP5x |
| <a href="#">EMT-160</a><br><a href="#">II 2G</a><br><a href="#">c T3</a><br><a href="#">IP5X</a>                        | 2.2 | 400V | 4.7  | 2860 | 2040 | 2250 | 39   | --- | -20 +60 | IP5x |
| <a href="#">EMT-160</a><br><a href="#">II 2G</a><br><a href="#">c T4</a><br><a href="#">IP5X</a>                        | 2.2 | 400V | 4.64 | 2860 | 2040 | 2250 | 64.7 | --- | -20 +60 | IP5x |
| <a href="#">EMT-160</a><br><a href="#">II 3G</a><br><a href="#">c T3</a><br><a href="#">IP5X</a>                        | 2.2 | 400V | 4.7  | 2860 | 2040 | 2250 | 39   | --- | -20 +60 | IP5x |
| <a href="#">EMT-90 II</a><br><a href="#">2D c</a><br><a href="#">T130</a><br><a href="#">C</a><br><a href="#">ATEX</a>  | 1.1 | 400V | 2.42 | 2780 | 1220 | 2150 | 20.2 | --- | -20 +60 | IP5x |
| <a href="#">EMT-90 II</a><br><a href="#">2G c</a><br><a href="#">T3</a><br><a href="#">IP5X</a>                         | 1.1 | 400V | 2.4  | 2780 | 1220 | 2150 | 21   | --- | -20 +60 | IP5x |
| <a href="#">EMT-90 II</a><br><a href="#">2G c</a><br><a href="#">T4</a><br><a href="#">IP5X</a>                         | 1.1 | 400V | 2.47 | 2780 | 1220 | 2150 | 36   | --- | -20 +60 | IP5x |
| <a href="#">EMT-90 II</a><br><a href="#">3G c</a>   | 1.1 | 400V | 2.4  | 2780 | 1220 | 2150 | 21   | --- | -20 +60 | IP5x |



|   |             |             |             |             |            |             |             |            |                |             |
|---|-------------|-------------|-------------|-------------|------------|-------------|-------------|------------|----------------|-------------|
| <a href="#"><u>T3</u></a><br><a href="#"><u>IP5X</u></a>  |             |             |             |             |            |             |             |            |                |             |
| <a href="#"><u>EMT-50 II</u></a><br><a href="#"><u>2D c</u></a><br><a href="#"><u>T130</u></a><br><a href="#"><u>C</u></a><br><a href="#"><u>ATEX</u></a> | <b>0.55</b> | <b>400V</b> | <b>1.37</b> | <b>2720</b> | <b>690</b> | <b>2100</b> | <b>15.4</b> | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-50 II</u></a><br><a href="#"><u>2G c</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5X</u></a>                               | <b>0.55</b> | <b>400V</b> | <b>1.4</b>  | <b>2720</b> | <b>690</b> | <b>2100</b> | <b>16</b>   | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-50 II</u></a><br><a href="#"><u>2G c</u></a><br><a href="#"><u>T4</u></a><br><a href="#"><u>IP5X</u></a>                               | <b>0.55</b> | <b>400V</b> | <b>1.39</b> | <b>2720</b> | <b>690</b> | <b>2100</b> | <b>29.9</b> | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-50 II</u></a><br><a href="#"><u>3G c</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5X</u></a>                               | <b>0.55</b> | <b>400V</b> | <b>1.4</b>  | <b>2720</b> | <b>690</b> | <b>2100</b> | <b>16</b>   | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-25 II</u></a><br><a href="#"><u>2D c</u></a><br><a href="#"><u>T110</u></a><br><a href="#"><u>C</u></a><br><a href="#"><u>ATEX</u></a> | <b>0.25</b> | <b>400V</b> | <b>0.69</b> | <b>2770</b> | <b>460</b> | <b>1350</b> | <b>9.4</b>  | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-25 II</u></a><br><a href="#"><u>2G c</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5X</u></a>                               | <b>0.25</b> | <b>400V</b> | <b>0.7</b>  | <b>2770</b> | <b>460</b> | <b>1350</b> | <b>9.8</b>  | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-25 II</u></a><br><a href="#"><u>2G c</u></a><br><a href="#"><u>T4</u></a><br><a href="#"><u>IP5X</u></a>                               | <b>0.37</b> | <b>400V</b> | <b>0.99</b> | <b>2770</b> | <b>460</b> | <b>1350</b> | <b>26</b>   | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-25 II</u></a><br><a href="#"><u>3G c</u></a><br><a href="#"><u>T3</u></a><br><a href="#"><u>IP5X</u></a>                               | <b>0.25</b> | <b>400V</b> | <b>0.7</b>  | <b>2770</b> | <b>460</b> | <b>1350</b> | <b>9.8</b>  | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-03 II</u></a><br><a href="#"><u>2D c</u></a><br><a href="#"><u>T110</u></a><br><a href="#"><u>C</u></a><br><a href="#"><u>ATEX</u></a> | <b>0.18</b> | <b>400V</b> | <b>0.5</b>  | <b>2820</b> | <b>410</b> | <b>1200</b> | <b>8.8</b>  | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |
| <a href="#"><u>EMT-03 II</u></a><br><a href="#"><u>2G c</u></a><br><a href="#"><u>T3</u></a>  | <b>0.18</b> | <b>400V</b> | <b>0.5</b>  | <b>2770</b> | <b>410</b> | <b>1200</b> | <b>9.2</b>  | <b>---</b> | <b>-20 +60</b> | <b>IP5x</b> |

|   |       |                 |       |           |         |        |        |          |         |             |
|---|-------|-----------------|-------|-----------|---------|--------|--------|----------|---------|-------------|
| <a href="#">IP5X</a>                      |       |                 |       |           |         |        |        |          |         |             |
| <a href="#">EMT-03 II 2G c T4 IP5X</a>    | 0.37  | 400V            | 0.99  | 2770      | 410     | 1200   | 25.8   | ---      | -20 +60 | IP5x        |
| <a href="#">EMT-03 II 3G c T3 IP5X</a>    | 0.18  | 400V            | 0.5   | 2770      | 410     | 1200   | 9.2    | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-6-450 II 2G c T3 IP5X</a> | 5.5   | 230/400V, 50 Hz | 11.6  | 950       | 14500   | 6.4    | 155    | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-4-400 II 2G c T3 IP5X</a> | 7.5   | 230/400V, 50 Hz | 14.6  | 1450      | 11600   | 1200   | 140    | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-6-400 II 2G c T3 IP5X</a> | 2.2   | 230/400V, 50 Hz | 5.1   | 960       | 800     | 2080   | 102    | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-4-315I I2Gc T3IP 5X</a>   | 3     | 230/400V, 50 Hz | 6.9   | 1415      | 6700    | 750    | 115    | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-6-315I I2Gc T3IP 5X</a>   | 0.75  | 230/400V, 50 Hz | 2.1   | 915       | 4400    | 350    | 65     | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-2-250 II 2G c T3 IP5X</a> | 5.5   | 230/400V, 50 Hz | 10.4  | 2915      | 6100    | 1750   | 95     | ---      | -20 +60 | IP5x        |
| <a href="#">ELF-4-250 II 2G c T3 IP5X</a> | 0.75  | 230/400V, 50 Hz | 2.1   | 1370      | 3300    | 470    | 50     | ---      | -20 +60 | IP5x        |
| Tipas                                     | Galia | Įtampa          | Srovė | Apsisukim | Našumas | Slėgis | Svoris | Triukšmo | Srauto  | Variklio IP |

|   | (kW) | (V)             | (A) | ai (x/min) | (m <sup>3</sup> /h) | (max Pa) | (kg) | lygis (dB) | max temperatūra (C) |      |
|---|------|-----------------|-----|------------|---------------------|----------|------|------------|---------------------|------|
| <a href="#">ELF-2-225 II 2G c T3 IP5X</a>   | 2.4  | 230/400V, 50 Hz | 4.8 | 2905       | 3500                | 1600     | 55   | ---        | -20 +60             | IP5x |
| <a href="#">ELF-4-225 II 2G c T3 IP5X</a>   | 0.55 | 230/400V, 50 Hz | 1.6 | 1370       | 2100                | 400      | 39   | ---        | -20 +60             | IP5x |
| <a href="#">ELF-2-200 II 2G c T3 IP5X</a>   | 1.5  | 230/400V, 50 Hz | 3.5 | 2850       | 2350                | 1300     | 33   | ---        | -20 +60             | IP5x |
| <a href="#">ELF-4-200 II 2G c T3 IP5X</a>   | 0.37 | 230/400V, 50 Hz | 1.3 | 1350       | 1400                | 400      | 28   | ---        | -20 +60             | IP5x |
| <a href="#">ELF-2-180I I2Gc T3IP 5X</a>     | 0.75 | 230/400V, 50 Hz | 1.8 | 2760       | 1800                | 1050     | 16   | ---        | -20 +60             | IP5x |
| <a href="#">ELF-4-180I I2Gc T3IP 5X</a>     | 0.25 | 230/400V, 50 Hz | 0.8 | 1350       | 950                 | 260      | 13   | ---        | -20 +60             | IP5x |
| <a href="#">ELF-2-160I I2Gc T3IP 5X</a>     | 0.37 | 230/400V, 50 Hz | 1   | 2680       | 850                 | 870      | ---  | ---        | -20 +60             | IP5x |
| <a href="#">ELF-2-160I I2Gc T3IP 5X (2)</a> | 0.55 | 230/400V, 50 Hz | 1.4 | 2720       | 1450                | 870      | ---  | ---        | -20 +60             | IP5x |
| <a href="#">ELF-4-160I</a>                  | 0.12 | 230/400V, 50 Hz | 0.5 | 1380       | 680                 | 220      | 9    | ---        | -20 +60             | IP5x |

|   |      |                 |      |      |      |     |      |     |         |      |
|---|------|-----------------|------|------|------|-----|------|-----|---------|------|
| <a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>  |      |                 |      |      |      |     |      |     |         |      |
| <a href="#">ELF-2-146I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>                        | 0.25 | 230/400V, 50 Hz | 0.7  | 2770 | 800  | 720 | 8.5  | --- | -20 +60 | IP5x |
| <a href="#">ELF-2-146I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a><br><a href="#">(2)</a> | 0.37 | 230/400V, 50 Hz | 1    | 2680 | 1100 | 720 | 10.5 | --- | -20 +60 | IP5x |
| <a href="#">ELF-4-146I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>                        | 0.06 | 230/400V, 50 Hz | 0.27 | 1400 | 530  | 400 | 8    | --- | -20 +60 | IP5x |
| <a href="#">ELF-2-133I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>                        | 0.18 | 230/400V, 50 Hz | 0.5  | 2710 | 700  | 550 | 7.8  | --- | -20 +60 | IP5x |
| <a href="#">ELF-2-133I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a><br><a href="#">(2)</a> | 0.25 | 230/400V, 50 Hz | 0.7  | 2770 | 900  | 550 | 8.6  | --- | -20 +60 | IP5x |
| <a href="#">ELF-4-133I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>                        | 0.06 | 230/400V, 50 Hz | 0.27 | 1400 | 420  | 145 | 6.9  | --- | -20 +60 | IP5x |
| <a href="#">ELF-2-120I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>                        | 0.12 | 230/400V, 50 Hz | 0.47 | 2810 | 560  | 410 | 6    | --- | -20 +60 | IP5x |
| <a href="#">ELF-4-120I</a><br><a href="#">I2Gc</a><br><a href="#">T3IP</a><br><a href="#">5X</a>                        | 0.06 | 230/400V, 50 Hz | 0.27 | 1400 | 280  | 105 | 6    | --- | -20 +60 | IP5x |
| <a href="#">ELF-2-</a>  | 0.09 | 230/400V, 50    | 0.33 | 2800 | 390  | 320 | 5    | --- | -20 +60 | IP5x |

|  |             |                        |             |             |            |           |          |              |                |             |
|--|-------------|------------------------|-------------|-------------|------------|-----------|----------|--------------|----------------|-------------|
| <a href="#"><u>108I</u></a><br><a href="#"><u>I2Gc</u></a><br><a href="#"><u>T3IP</u></a><br><a href="#"><u>5X</u></a>   |             | <b>Hz</b>              |             |             |            |           |          |              |                |             |
| <a href="#"><u>ELF-</u></a><br><a href="#"><u>4-</u></a><br><a href="#"><u>108I</u></a><br><a href="#"><u>I2Gc</u></a><br><a href="#"><u>T3IP</u></a><br><a href="#"><u>5X</u></a> | <b>0.06</b> | <b>230/400V, 50 Hz</b> | <b>0.27</b> | <b>1400</b> | <b>200</b> | <b>80</b> | <b>5</b> | <b>- - -</b> | <b>-20 +60</b> | <b>IP5x</b> |